

MC 58

EIGHT CHANNEL POWER AMPLIFIER

CONFIGURABLE TO 7, 6, 5 OR 4 CHANNELS

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. 4 **POWER** indicator lights indicate when each channel pair is active. ⚡ **POWER GUARD** lights for channels **ONE, TWO, THREE, FOUR, FIVE, SIX, SEVEN** and **EIGHT**. Remote ON indicator light. **POWER** switch: ON or OFF.



BACK PANEL: **POWER CONTROL:** LOCAL or REMOTE. Power cord receptacle. FUSE. [Channels 8 and 7 section: **INPUT** and **OUTPUT:** 8 and 7/**BRIDGED**. 8 and 7/**BRIDGED** LEVEL controls: 2.5V to 1.0V. **MODE** switch: **BRIDGED, STEREO** or **MONO**. Speaker output terminals: 8 and 7.] [Channels 6 and 5 section: **INPUT** and **OUTPUT:** 6 and 5/**BRIDGED**. 6 and 5/**BRIDGED** LEVEL controls: 2.5V to 1.0V. **MODE** switch: **BRIDGED, STEREO** or **MONO**. Speaker output terminals: 6 and 5.] **8 CHANNEL IN** 25 pin connector. **POWER CONTROL** jacks: **IN** and **OUT**. **MULTI-ROOM** DIN connector. [Channels 4 and 3 section: **INPUT** and **OUTPUT:** 4 and 3/**BRIDGED**. 4 and 3/**BRIDGED** LEVEL controls: 2.5V to 1.0V. **MODE** switch: **BRIDGED, STEREO** or **MONO**. Speaker output terminals: 4 and 3.] [Channels 2 and 1 section: **INPUT** and **OUTPUT:** 2 and 1/**BRIDGED**. 2 and 1/**BRIDGED** LEVEL controls: 2.5V to 1.0V. **MODE** switch: **BRIDGED, STEREO** or **MONO**. Speaker output terminals: 2 and 1.]

SPECIFICATIONS: Eight channels. **50w/ch** into 4 ohms and **30w/ch** into 8 ohms. (**100w** into 8 ohms mono with 2 channels bridged). Response 20-20kHz (+0 - 0.25dB). Distortion 0.005%. Noise and hum -92dBA. Output direct coupled for 4 to 8 ohms. Damping factor 100 at 4 ohms and 200 at 8 ohms. Input impedance 20k. Input sensitivity 1v. *Sentry Monitor. Power Guard.*

MC 58

EIGHT CHANNEL POWER AMPLIFIER

CONFIGURABLE TO 7, 6, 5 OR 4 CHANNELS

McIntosh

The Compendium



MC 58 - Sold from 200? - . S/N: ?????~?????

Size 7-1/16"H, 17-1/2"W and 20"D. Weight 40 lb.

\$2,600.00