

# C 26

## STEREO PRE-AMPLIFIER

# McIntosh

## The Compendium



**FRONT PANEL:** Glass with illuminated teal/gold nomenclature. **INPUT SELECTOR:** AUX, TAPE 2, TAPE 1, TUNER, PHONO 1, and PHONO 2. **MODE SELECTOR:** L TO L+R, R TO L+R, STEREO REVERSE, STEREO, MONO (L+R), L+R TO L and L+R TO R. Power indicator light. **VOLUME** with on-OFF switch. ⚡ Pushbutton switches: **MONITOR:** TAPE 1 IN or OUT, TAPE 2 IN or OUT. **FILTERS:** LF IN or OUT, HF: IN or OUT, **MAIN SPEAKER:** ON or OFF, **REMOTE SPEAKER:** ON or OFF. **HEADPHONES** jack. **LOUDNESS:** FLAT to MAX. **BALANCE:** L to R. Dual concentric **BASS** control. Dual concentric **TREBLE** control. **PANLOC** buttons.



**BACK PANEL:** LEFT & RIGHT push terminals for **AMPLIFIER OUTPUT**, **MAIN SPEAKERS** and **REMOTE SPEAKERS**. **INPUTS:** AUX, TAPE 2, TAPE 1, TUNER, PH 1 and PH 2. ⚡ **FUSE**. Power cord. **AC OUTLETS:** 1 unswitched, 4 switched. **OUTPUTS:** L+R, MAIN (2 pair). **GROUND** binding post. **OUTPUTS:** TAPE 1 and 2. Panloc mounting.



**TOP PANEL:** **PHASE CONTROL:** 180° or 0° NORMAL. **CENTER CHANNEL LEVEL:** MIN. to MAX.

**SPECIFICATIONS:** Response 20-20kHz (+0 -0.5dB). Distortion 0.1%. Noise and hum - 85dB aux, -74dB phono. Output rated 2.5v, 10v max. Output impedance 200 ohms. Load impedance 47k. Input sensitivity and impedance: aux 0.25V at 250k, phono 2mV at 47k. Center channel out (L+R) 2.5v with control (+6 -6 dB re main output). Tone controls: bass +16dB to -20dB, treble +20 to -20dB. Loudness continuously variable. LF filter 50Hz at 6dB/octave. HF filter 5kHz at 6dB/octave. Voltage gain 20dB aux, 62dB phono. Switch for power amp output to main and/or remote speakers.

# C 26

## STEREO PRE-AMPLIFIER

# McIntosh

## The Compendium



**C 26** - Sold from April 1968 - 1977. S/N: 10P01~99P99 & AG1001~AG7398 (15,208 UNITS)

Size 5-7/16"H, 16"W and 13"D behind panel. Weight 18 lb. **\$449.00**