

MA 6850

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Left and right **POWER OUTPUT** meters (linear **WATTS** or **DECIBELS**). ⚡ **TREBLE**. **RECORD SELECTOR** with indicator lights: **AUX**, **CD 1**, **CD 2**, **TUNER**, **TAPE 1**, **TAPE 2**, **TAPE 3**, **VIDEO**. Left **POWER GUARD** light. IR sensor. Digital **VOLUME** readout. Right **POWER GUARD** light. **LISTEN SELECTOR** with indicator lights: **AUX**, **CD 1**, **CD 2**, **tuner**, **TAPE 1**, **TAPE 2**, **TAPE 3**, **VIDEO**. **VOLUME**. ⚡ **BASS**. Pushbutton switches with indicator lights: **MONO**, **LISTEN PROC**, **RECORD PROC**, **RECORD MON**. **POWER**: **OFF** or **ON**. Pushbutton switches with indicator lights: **MUTE**, **SPEAKERS 1** and **2**, and **STANDBY/ON**. Concentric **BALANCE / LOUDNESS**: **FLAT** to **MAX**.



BACK PANEL: **LISTEN** jacks: **POWER AMP IN**. **POWER AMP INPUT** switch: **EXTERNAL** or **INTERNAL**. **LISTEN** jacks: **PREAMP OUT**. **PROCESSOR**: **FROM** and **TO**. **RECORD** jacks: **TAPE 3**, **TAPE 2**, **TAPE 1**, **PROCESSOR**: **FROM** and **TO**. **INPUTS**: **VIDEO**, **TAPE 3**, **TAPE 2**, **TAPE 1**, **TUNER**, **CD 2**, **CD 1**, **AUX**. ⚡ Coax **EXTERNAL SENSOR** connector. speaker control relay connector. **POWER** control jack. **DATA PORTS**: **SUM**, **VIDEO**, **TAPE 3**, **TAPE 2**, **TAPE 1**, **TUNER**, **CD 2**, **CD 1**, **AUX**, **HOME**. ⚡ Power cord receptacle. **FUSE**. **RIGHT** output **SPEAKER** connectors for **2**, **4** and **8 ohms**. **LEFT** output **SPEAKER** connectors for **2**, **4** and **8 ohms**.

MA 6850

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: **150w/ch.** Response 20-20kHz (+0 -0.5dB). Distortion 0.005%. Output impedance 2, 4 and 8 ohms. Dynamic headroom 1.8dB. Noise and hum: 110dB power amp, -100dB high level, -90dB low level re 10mV. Damping factor 40. Input sensitivity and impedance: high level 0.25V (10V max) at 22k, power amp 1.4V. Bass and treble boost or cut 12dB. *Power Guard. Sentry Monitor.* Same as the **MA 6800** but without headphone output and phono preamp. Has hand remote **HR 033**.



MA 6850 - Sold from 1998 - . S/N: PE1001~?????

Size 7-1/16"H, 17-1/2"W and 20"D. Weight 70 lbs. **\$3,500.00**