

MC 205

FIVE CHANNEL POWER AMPLIFIER

CONFIGURABLE TO 3 + 2 CHANNELS

McIntosh

The Compendium



FRONT PANEL: Glass with LED/fiber-optic illuminated green/gold nomenclature. 3 POWER GUARD lights: channel 1, 3 and 5. ⚡ Three illuminated POWER OUTPUT meters (linear WATTS or DECIBELS): channel 1, 3, and 5. ⚡ 2 POWER GUARD lights: channel 2 and 4. ⚡ Remote ON indicator light. ⚡ METER LIGHT switch: ON or OFF. POWER switch: ON or OFF STANDBY.



BACK PANEL: Speaker OUTPUTS connectors: 5 - Right Front, 2 - Right Back and 4 - Left Back. ↗ 1 - Left Front, 3 - center. ⚡ Power cord receptacle. FUSE. IMPEDANCE switch: 4, or 8 Ω . POWER CONTROL jacks: IN and OUT. INPUTS: channel 4 - Left Back balanced, channels 2 - Right Back and 4 - Left Back unbalanced, channel 2 - Right Back balanced. Channel 5 - Right Front unbalanced, channels 5 - Right Front and 3 - center balanced, channels 1 - Left Front and 3 - center unbalanced, channel 1 - Left Front balanced.

SPECIFICATIONS: Five channels. **200w/ch** into 4 or 8 ohms. Response 20-20kHz (+0 -0.25dB). Distortion 0.005%. Noise and hum -112dBA. Output impedance 4 or 8 ohms. Damping factor >70 at 4 ohms or 140 at 8 ohms. Input impedance 10k unbalanced and 20k balanced. Input sensitivity 1v w/4ohm, 1.4v w/8ohm, balanced, and 2v w/4ohm, 2.8v w/8ohm, unbalanced. Dynamic headroom: 1.7 dB. *Dynamic Power Manager. Sentry Monitor. Power Guard.* Power requirements 120V at 10 Amps.

MC 205

FIVE CHANNEL POWER AMPLIFIER

CONFIGURABLE TO 3 + 2 CHANNELS

McIntosh

The Compendium



MC 205 - Sold from March 2007 - . S/N: ??1001~?????

Size 9-7/16"H, 17-1/2"W and 21"D. Weight 81 lb. **\$6,000.00**