

# MC 206

## 6 CHANNEL POWER AMPLIFIER

McIntosh

The Compendium



**FRONT PANEL:** Glass with illuminated teal/gold nomenclature. 6 POWER GUARD lights – one for each channel. 6 meter lights – indicates which channel the meter is reading – LEFT FRONT, LEFT SURROUND, CENTER, BACK SURROUND, RIGHT FRONT, RIGHT SURROUND. ⚡ Three switchable illuminated POWER OUTPUT meters (linear WATTS). ⚡ METER switch: LIGHTS OFF, SUMMED, FRONT / CTR, SURR. Remote ON indicator. POWER switch: OFF, REMOTE or ON.



**BACK PANEL:** Power cord receptacle. FUSE. [Right front and surround section: RIGHT SURROUND and RIGHT FRONT INPUTS. RIGHT SURROUND and RIGHT FRONT LEVEL controls: 2.5V to 1.0V. Speaker OUTPUTS terminals: RIGHT SURROUND and RIGHT FRONT]. [Back surround and center channel section: BACK SURROUND and CTR INPUT. BACK SURROUND and center LEVEL controls: 2.5V to 1.0V. Speaker OUTPUTS terminals: BACK SURROUND and center]. MULTI-CHANNEL 26 pin INPUT connector. POWER CONTROL jacks: IN and OUT. [Left surround and front section: LEFT SURROUND and LEFT FRONT INPUTS. LEFT SURROUND and LEFT FRONT LEVEL controls: 2.5V to 1.0V. Speaker OUTPUT terminals: LEFT SURROUND and LEFT FRONT].

**SPECIFICATIONS:** 200w/ch into 4 ohms or 120w/ch into 8 ohms. Response 20-20kHz (+0 -0.25dB). Distortion 0.005%. Noise and hum -113dBA. Damping factor 100 at 4 ohms and 200 at 8 ohms. Input impedance 10k ohms. Input sensitivity 1,0V. Sentry Monitor. Power Guard. Power requirements 120V at 11 Amps.

# MC 206

6 CHANNEL POWER AMPLIFIER

McIntosh  
The Compendium

---



**MC 206** - Sold from 200? - . S/N: TK1001~?????

Size 7-1/8"H, 17-1/2"W and 18"D. Weight 57 lb. **\$4,600.00**