

MC 2102

STEREO POWER AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. METER switch: LIGHTS OFF, WATTS or HOLD. Illuminated left and right POWER OUTPUT meters (linear WATTS, DECIBELS and BIAS SET). Remote ON indicator light. POWER switch: OFF, REMOTE or ON. Tubes can be seen through the clear rectangle above the meters.



BACK PANEL: Polished stainless steel chassis. Power cord receptacle. FUSE. RIGHT channel OUTPUT binding posts for 2 Ω , 4 Ω or 8 Ω speakers. LEFT channel OUTPUT binding posts for 2 Ω , 4 Ω or 8 Ω speakers. POWER CONTROL jacks: IN and OUT. INPUT switch: BALANCED or UNBALANCED. MODE switch: STEREO, PARALLEL or BRIDGED MONO. RIGHT audio INPUTS: UNBALANCED and BALANCED. LEFT audio INPUTS: BALANCED and UNBALANCED.

SPECIFICATIONS: 100w/ch into 2, 4 or 8 ohms. Response 20-20kHz (+0 -0.25dB). Distortion 0.5%. Noise and hum -100dBA. Damping factor greater than 18. Input impedance 20k unbalanced, 40k balanced. Input sensitivity 2.5V for balanced or 5.0V for unbalanced. Power requirements 120V at 5 Amps.

TUBES: 8-KT88/6550 output, 4-12AX7A, 2-12AT7. Solid state rectifier bridges.

MC 2102

STEREO POWER AMPLIFIER

McIntosh
The Compendium



MC 2102 - Sold from 2002 - . S/N: ?????~?????

Size 10-1/8"H, 17-3/4"W and 16"D. Weight 88 lb. **\$6,100.00**