

MC 352

STEREO POWER AMPLIFIER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Illuminated POWER OUTPUT meters (linear WATTS or DECIBELS). LEFT and RIGHT POWER GUARD lights. Remote ON indicator. ⚡ METER switch: LIGHTS OFF, WATTS or HOLD. POWER switch: OFF, REMOTE or ON.



BACK PANEL: POWER CONTROL jacks: OUT and IN. BALANCED Right/MONO and Left INPUTS. UNBALANCED Left and Right/MONO INPUTS. INPUT MODE switch: BALANCED or UNBALANCED. ⚡ Power cord receptacle. FUSE. Gold plated RIGHT channel OUTPUT terminals for 4, or 8 Ω speakers. OUTPUT MODE switch: MONO/PARALLEL or STEREO. RIGHT and LEFT gold plated speaker OUTPUT terminals for 2 Ω . Gold plated LEFT channel OUTPUT terminals for 4, or 8 Ω speakers.

SPECIFICATIONS: 350w/ch into 2, 4 or 8 ohms. (700w mono). Response 20-20kHz (+0 -0.25dB). Distortion 0.005%. Signal to noise ratio 85dBA unbalanced (116dBA below rated output), 115dBA balanced (124dBA below rated output). Output impedance 2, 4 and 8 ohms. (1, 2, and 4 ohms in mono). Damping factor 40. Dynamic headroom 2.1dB. Input impedance 20k unbalanced, 40k balanced. Input sensitivity: 1.9V unbalanced, 3.8V balanced. Sentry Monitor. Power Guard.

MC 352

STEREO POWER AMPLIFIER

McIntosh
The Compendium



MC 352 - Sold from 1998 - . S/N: ?????~?????

Size 8-7/8"H, 17-1/2"W and 21"D. Weight 105 lbs. **\$4,500.00**