

MC 40

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



CONTROLS & CONNECTORS: Chrome/black chassis. Line OUTPUTS octal socket for 70V/600 OHM output. SPEAKER OUTPUT barrier strip for 4, 8 and 16 OHMS. GAIN control. ⚡ Power cord. FUSE. AC outlet. LINE VOLTAGE switch: 117 or 125V. Audio INPUT.



SPECIFICATIONS: 40w. Response 20-20kHz (+0 -0.1dB). Distortion 0.5%. Noise & hum -90dB. Output impedance 4, 8, 16, 125, 150 and 600 ohms. 600 ohm balanced to ground and center tapped. 4, 8 and 16 ohms isolated from ground. Output voltages 25 and 70.7V. Internal impedance less than 10% of rated impedance. Input impedance 250k. Input sensitivity 0.5V (2.0V with gain control switched at maximum).


TUBES: 2-6L6GC output, 2-12AX7, 12AU7, 12BH7. Solid state rectifier bridge.



MC 40

MONAURAL POWER AMPLIFIER

McIntosh
The Compendium



MC 40 - Sold from May 1962 - April 1969. S/N: 100L1~552L9 (8,444 UNITS)

Size 7-7/8"H, 8-1/8"W and 13-3/4"D. Weight 30 lb. **\$159.00**