

MC 602

STEREO POWER AMPLIFIER

McIntosh
The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Illuminated **left and right POWER OUTPUT** meters (linear **WATTS** or **DECIBELS**). **Left and right POWER GUARD** lights. ⚡ **METER** switch: **LIGHTS OFF**, **WATTS** or **HOLD**. Remote ON indicator light. **POWER** switch: **OFF**, **REMOTE** or **ON**.



BACK PANEL: **POWER CONTROL** jacks: **OUT** and **IN**. **LEFT** and **RIGHT BALANCED** INPUTS. **LEFT** and **RIGHT UNBALANCED** INPUTS. **INPUT MODE** switch: **BALANCED** or **UNBALANCED**. ⚡ Polished stainless steel chassis. **CIRCUIT BREAKER**. Gold plated **RIGHT** channel **OUTPUT** terminals for **2**, **4**, or **8 Ω** speakers. Gold plated **LEFT** channel **OUTPUT** terminals for **2**, **4**, or **8 Ω** speakers. Power cord receptacle.

MC 602

STEREO POWER AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 600w/ch into 2, 4 or 8 ohms. Response 20-20kHz (+0 -0.25dB). Distortion 0.005%. Signal to Noise Ratio -124dBA balanced, -120dBA unbalanced. Output impedance 2, 4, or 8 ohms. Damping factor 100 at 8 ohms. Input impedance 10K balanced and 20K unbalanced. Input sensitivity 4.9v balanced and 2.45v unbalanced. Dynamic headroom 2.1 dB. *Sentry Monitor. Power Guard.* Power requirements 120V at 15 Amps.



MC 602 - Sold from 2003 - . S/N: RX1001~?????

Size 11"H, 17-3/4"W and 19.63"D. Weight 155 lbs.

\$8,100.00