

# MC 7106

## SIX CHANNEL POWER AMPLIFIER

McIntosh

The Compendium



**FRONT PANEL:** Glass with illuminated teal/gold nomenclature. Power indicator light. ⚡ Channel ONE and TWO POWER GUARD lights. Channel THREE and FOUR POWER GUARD lights. ⚡ Channel FIVE and SIX POWER GUARD lights. ⚡ Six LED POWER LEVEL columns in X10 increments from .01W to 100W for each channel.



**BACK PANEL:** POWER switch: ON or OFF/REMOTE. FUSE. Power cord. [Channels 6 and 5 section: INPUTS: 6 and 5 / BRIDGED. 6 and 5 / BRIDGED LEVEL controls: 2.5V to 1.0V THX. MODE switch: NORMAL or BRIDGED. Speaker OUTPUTS terminals: 6 and 5]. DISPLAY BRIGHTNESS control: MAXIMUM to OFF. POWER CONTROL jacks: IN and OUT. [Channels 4 and 3 section: INPUTS: 4 and 3 / BRIDGED. 4 and 3 / BRIDGED LEVEL controls: 2.5V to 1.0V THX. MODE switch: NORMAL or BRIDGED. Speaker OUTPUTS terminals: 4 and 3]. THX 25 pin INPUT connector. [Channels 2 and 1 section: INPUTS: 2 and 1 / BRIDGED. 2 and 1 / BRIDGED LEVEL controls: 2.5V to 1.0V THX. MODE switch: NORMAL or BRIDGED. Speaker OUTPUTS terminals: 2 and 1].

**SPECIFICATIONS:** Six channels. **160w/ch** into 8 ohms or **150w** into 4 ohms. (**300w** into 8 ohms mono with 2 channels bridged). Response 20-20kHz (+0 -0.25dB). Distortion 0.005%. Noise and hum -113dBA. Output direct coupled for 4 to 8 ohms. Damping factor 100 or greater. Input impedance 20k. Input sensitivity 1v. *Sentry Monitor. Power Guard. THX approved.*

# MC 7106

SIX CHANNEL POWER AMPLIFIER

McIntosh  
The Compendium



**MC 7106** - Sold from 1992 - . S/N: HE1001~?????

Size 7-1/8"H, 17-1/2"W and 20"D. Weight 52 lb. **\$3,500.00**