

# MC 7205

## FIVE CHANNEL POWER AMPLIFIER

McIntosh

The Compendium



**FRONT PANEL:** Glass with illuminated teal/gold nomenclature. 5 POWER GUARD lights – one for each channel. 6 meter lights – indicates which channel the meter is reading. ⚡ Three switchable illuminated POWER OUTPUT meters (linear WATTS). ⚡ METER switch: LIGHTS OFF, SUMMED, FRONT / CTR, SURR / SUB. POWER switch: OFF, REMOTE or ON.



**BACK PANEL:** Power cord receptacle. FUSE. [Right front and surround section: RIGHT FRONT and RIGHT SURROUND INPUTS. RIGHT SURROUND and RIGHT FRONT LEVEL controls: 2.5V to 1.0V. Speaker output terminals: RIGHT SURROUND and RIGHT FRONT]. [Subwoofer and center channel section: SUB IN/OUT and CTR INPUT. SUB METER CAL and center LEVEL controls: 2.5V to 1.0V. Speaker output terminal: center]. THX 26 pin INPUT connector. POWER CONTROL jacks: IN and OUT. [Left surround and front section: LEFT SURROUND and LEFT FRONT INPUTS. LEFT SURROUND and LEFT FRONT LEVEL controls: 2.5V to 1.0V. Speaker output terminals: LEFT SURROUND and LEFT FRONT].

**SPECIFICATIONS:** Five channels. **200w/ch** into 4 ohms. **120w/ch** into 8 ohms. Response 20-20kHz (+0 -0.25dB). Distortion 0.005%. Noise and hum -113dBA. Output impedance 4 or 8 ohms. Damping factor 100 at 4 ohms or 200 at 8 ohms. Input impedance 10k. Input sensitivity 1v. *Sentry Monitor. Power Guard. THX Certified.*



# MC 7205

## FIVE CHANNEL POWER AMPLIFIER

# McIntosh

## The Compendium



**MC 7205** - Sold from 1998 - . S/N: NJ1001~?????  
Size 7-1/16"H, 17-1/2"W and 21"D. Weight 53 lb. **\$4,500.00**