

MC 75

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



CONTROLS & CONNECTORS: Chrome/black chassis. Octal socket for 70V/600 OHM OUTPUTS. SPEAKER OUTPUT barrier strip for 4, 8 and 16 OHMS. GAIN control with 2.0 V SETTING FOR MCINTOSH PREAMP. ⚡ Power cord. FUSE. AC outlet. LINE VOLTAGE switch: 117 or 125V. 0.5 VOLT audio INPUT.



SPECIFICATIONS: 75w. Response 16-40kHz (+0 -0.1dB). Distortion 0.5%. Noise & hum -90dB. Output impedance 4, 8, 16, 67, 150 and 600 ohms. 600 ohm balanced to ground. 4, 8 and 16 ohms isolated from ground. Output voltages 25, 70.7, 115 and 230V. 230V winding center tapped. Internal impedance less than 10% of rated impedance. Input impedance 250k. Input sensitivity 0.5V (2.0V with gain control switched at maximum).

TUBES: 2-KT88/6550 output, 12AX7, 12AU7, 12BH7, 12AZ7 or 12AT7. Solid state rectifier.

MC 75

MONAURAL POWER AMPLIFIER

McIntosh
The Compendium



MC 75 - Sold from June 1961 - May 1970. S/N: 100B1~632B0 (9,981 UNITS)
Size 8-1/4"H, 8-1/4"W and 16-3/4"D. Weight 44 lb. **\$229.00**