

C 15

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. **BASS.** **TREBLE.** **BALANCE:** L to R. **VOLUME.** ⚡ **IR SENSOR.** Touch buttons (with indicator lights): **CD 1, CD 2, TUNER, VIDEO, PH/AUX, TAPE.** **HEADPHONES** jack. Touch buttons (with indicator lights): **MONO, OUTPUT 1, OUTPUT 2, MUTE, LOUD, STANDBY/ON.** **POWER:** ON or OFF.



BACK PANEL: Power cord receptacle. Coax **EXTERNAL SENSOR** connector. **POWER CONTROL** jack. **DATA PORTS:** **VIDEO / SUM, TUNER / HOME, CD 2 / TAPE, CD 1 / AUX.** **OUTPUTS:** 2, 1 and TAPE. **PROCESSOR FROM.** **PROCESSOR** switch IN or OUT. **PROCESSOR TO.** **INPUTS:** TAPE, VIDEO, TUNER, CD 2, CD 1, PH/AUX. **GROUND** binding post. **Switch:** PH or AUX.

SPECIFICATIONS: Response 20-20kHz (+0 -0.5dB). Distortion 0.002%. Noise and hum -105dB high level, -90dB phono. Output impedance 600 ohms. Input sensitivity and impedance: high level 0.25V (10V max) and 22k, phono 2.5mV (90mV max) at 47k and 65pF. Tone controls: bass and treble boost and cut 12dB. Electromagnetically switched inputs. Uses **HR 033** hand remote control.

C 15

STEREO PRE-AMPLIFIER

McIntosh

The Compendium



C 15 - Sold from 1998 - . S/N: ?????~?????

Size 5-3/8"H, 17-1/2"W and 17-1/2"D behind panel. Shipping weight 14.5 lb.

\$1,500.00