

MA 6800

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium



FRONT PANEL: Glass with illuminated teal/gold nomenclature. Left and right **POWER OUTPUT** meters (linear WATTS or DECIBELS). ⚡ **TREBLE**. **RECORD SELECTOR** with indicator lights: PH/AUX, CD 1, CD 2, TUNER, TAPE 1, TAPE 2, TAPE 3, VIDEO. Left **POWER GUARD** light. IR sensor. Digital **VOLUME** readout. Right **POWER GUARD** light. **LISTEN SELECTOR** with indicator lights: PH/AUX, CD 1, CD 2, tuner, TAPE 1, TAPE 2, TAPE 3, VIDEO. **VOLUME**. ⚡ **BASS**. Pushbutton switches with indicator lights: **MONO**, **LISTEN PROC**, **RECORD PROC**, **RECORD MON**. **HEADPHONES** jack. Pushbutton switches with indicator lights: **MUTE**, **SPEAKERS 1** and **2**, and **POWER**. Concentric **BALANCE / LOUDNESS**: FLAT to MAX.



BACK PANEL: **LISTEN** jacks: **POWER AMP IN**. **POWER AMP INPUT** switch: **EXTERNAL** or **INTERNAL**. **LISTEN** jacks: **PREAMP OUT**. **PROCESSOR**: **FROM** and **TO**. **RECORD** jacks: **TAPE 3**, **TAPE 2**, **TAPE 1**, **PROCESSOR**: **FROM** and **TO**. **INPUTS**: **VIDEO**, **TAPE 3**, **TAPE 2**, **TAPE 1**, **TUNER**, **CD 2**, **CD 1**, **AUX**, **PH**. **SELECTOR** switch: **AUX** or **PH**. ⚡ Coax **EXTERNAL SENSOR** connector. speaker control relay connector. **POWER** control jack. **DATA PORTS**: **SUM**, **VIDEO**, **TAPE 3**, **TAPE 2**, **TAPE 1**, **TUNER**, **CD 2**, **CD 1**, **AUX**, **HOME**. Ground binding post. ⚡ **Power cord** receptacle. **FUSE**. **AC outlets**: 1 **UNSWITCHED**, 6 **SWITCHED**. **RIGHT** output **SPEAKER** connectors for 2, 4 and 8 ohms. **LEFT** output **SPEAKER** connectors for 2, 4 and 8 ohms.

MA 6800

STEREO INTEGRATED AMPLIFIER

McIntosh

The Compendium

SPECIFICATIONS: 150w/ch. Response 20-20kHz (+0 -0.5dB). Distortion 0.005%. Output impedance 2, 4 and 8 ohms. Dynamic headroom 1.8dB. Noise and hum: 110dB power amp, -100dB high level, -90dB low level re 10mV. Damping factor 40. Input sensitivity and impedance: high level 0.25V (10V max) at 22k, phono 2.5mV (90mV max) at 47k and 65pF, power amp 1.4V. Bass and treble boost or cut 12dB. *Power Guard. Sentry Monitor.* Has hand remote **HR 033**.



MA 6800 - Sold from 1994 - . S/N: mc1001~?????

Size 7-1/16"H, 17-1/2"W and 20"D. Weight 70 lbs.

\$5,000.00