

# MC 207

## SEVEN CHANNEL POWER AMPLIFIER

# McIntosh

## The Compendium



**FRONT PANEL:** LED/fiber-optic illuminated green/gold nomenclature. 3 POWER GUARD lights – left front, center and right front. Three illuminated POWER OUTPUT meters (linear WATTS or DECIBELS): 1-LEFT FRONT, 4-CENTER, and 7-RIGHT FRONT. ⚡ 4 POWER GUARD lights – left surround, right surround, left back surround and right back surround. Remote ON indicator light. ⚡ METER LIGHTS switch: OFF or ON. POWER switch: OFF, REMOTE or ON.



**BACK PANEL:** Speaker OUTPUTS connectors: Right Front/channel 7, Right Back/channel 6, Left Back/channel 5. ↗ center/channel 4. ↗ Left Front/channel 1, Left surround/channel 2, Right surround/channel 3. ⚡ Polished stainless steel chassis. Power cord receptacle. CIRCUIT BREAKER. INPUTS: channel 7 balanced, channels 7 and 6 unbalanced, channels 6 and 5 balanced, channels 5 and 4 unbalanced, channels 4 and 3 balanced, channels 3 and 2 unbalanced, channels 2 and 1 balanced, channel 1 unbalanced. MULTICHANNEL 25 pin INPUT connector.

**SPECIFICATIONS:** Seven channels. **200w/ch** into 4 or 8 ohms. Response 20-20kHz (+0 -0.25dB). Distortion 0.005%. Noise and hum -112dBA. Output impedance 4 or 8 ohms. Damping factor >60 at 4 ohms or 140 at 8 ohms. Input impedance 10k unbalanced and 20k balanced. Input sensitivity 1v w/4ohm, 1.4v w/8ohm, balanced, and 2v w/4ohm, 2.8v w/8ohm. Dynamic headroom: 1.7 dB. *Dynamic Power Manager. Sentry Monitor. Power Guard.* Power requirements 120V at 12 Amps.

# MC 207

**SEVEN CHANNEL POWER AMPLIFIER**

# McIntosh

**The Compendium**

---

**MC 207** - Sold from August 2004 - . S/N: ?????~?????

Size 9-7/16"H, 17-1/2"W and 18-3/4"D. Weight 83 lb.

**\$6,000.00**