

MC 60

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



CONTROLS & CONNECTORS: Chrome/black chassis. Power cord. Speaker OUTPUT barrier strip for 4, 8 and 16 ohms as well as 0.5V INPUT. 0.5V INPUT. GAIN control. ⚡ FUSE. 3 AMP AC OUTLET. Octal OUTPUT socket powers **McIntosh C 8, C 4, C 104, or C 108** preamps. Octal socket PRE-AMP. INPUT. HUM ADJUSTment.



SPECIFICATIONS: 60w. Response 20-30kHz (+0.1 -0.1dB). Distortion 0.5%. Noise & hum - 90dB. Output impedance 4, 8, 16, and 600 ohms. 600 ohm balanced to ground. 4, 8 and 16 ohms isolated from ground. Damping factor 12 for 4, 8 and 16 ohms. Input impedance 500k. Input sensitivity 0.5V.



TUBES: 2-6550 output, 2-12AX7, 12AU7, 12BH7, 2-5U4.

MC 60

MONAURAL POWER AMPLIFIER

McIntosh

The Compendium



MC 60 - Sold from August 1955 - August 1961. S/N: 500~7,116 & 1F001~6F635
(5,625 UNITS)

Size 8"H, 10"W and 14"D. Weight 46 lb. **\$219.00**